# HP Laserlet 2400 Printer series





Experience high quality output and flexible features with this great with its network management tools<sup>1</sup>.



HP LaserJet 2420/n/dn Printer

Ideal for work teams of 2 – 12 users and professional individuals with advanced printing needs in any size office that require a value-packed, user-friendly black and white laser printer that delivers professional results instantly.

Increase the efficiency of your team with a reliable printer that requires lower user intervention.

- · Simplify print job management with an intuitive, two-line control panel, and a print cartridge that is easy to use and maintain.
- HP Smart Printing Technology<sup>2</sup> creates automatic alerts when the cartridge is low.
- The HP Embedded Web Server enables one-to-one network printer management, while HP Web Jetadmin<sup>1</sup> helps to manage fleets of peripherals.
- Network-ready models<sup>3</sup> include an HP Jetdirect Fast Ethernet Embedded Print Server, which leaves the EIO slot open for even more connectivity options.



HP LaserJet 2430t/tn/dtn Printer

#### Get consistently outstanding print quality without compromising performance.

- Create professional looking documents with crisp text and sharp graphics at true 1200 x 1200 dpi resolution at full engine speed.
- HP Smart Printing Technology<sup>2</sup> ensures printing properties are automatically adjusted for consistent quality and reliability.
- Increase efficiency with fast speeds up to 33 ppm and a first page out in less than 10 seconds with instant-on technology.
- Easily handle your most complex documents with the fast 400 MHz processor and expandable memory up to 320 MB.

### A value-packed printer that adapts easily to the changing needs of your business.

- Use a wide range of media types and sizes with a 100-sheet multipurpose input tray and 250-sheet input tray.
- Save time by increasing maximum input capacity to 850 sheets with the optional 500-sheet input tray<sup>4</sup>.
- Automatic two-sided printing<sup>5</sup> offers greater finishing capabilities and reduces paper consumption.
- Use the two CompactFlash™ slots for third-party solutions such as more font choices, intelligent e-forms, secure printing, barcode printing, SAP/ERP solutions, and job accounting solutions.



Management tools such as Web Jetadmin and Embedded Web Server are available on the HP LaserJet 2420n/dn and 2430tn/dtn models only.

<sup>&</sup>lt;sup>2</sup>Using genuine HP supplies ensures availability of all HP Smart Printing features.
<sup>3</sup>Embedded networking standard on HP LaserJet 2420n/dn and 2430tn/dtn models only.
<sup>4</sup>The 500-sheet input tray is an optional accessory on HP LaserJet 2420 Printer series, standard with 2430 Printer series.
<sup>5</sup>The automatic two-sided printing unit is available on the HP LaserJet 2420dn, and 2430dtn models only. It is not an optional accessory that can be added on to other models.

## **Technical specifications**

	HP LaserJet 2420 Printer series:	HP LaserJet 2430 Printer series:	
Print speed First page out	Up to 28 ppm Less than 10 secs Exact speed varies depending on the system configuration, software application, a	Up to 33 ppm Less than 10 secs and document complexity	Q5
Processor	400 MHz MIPS 20KC	400 MHz MIPS 20KC	
	Two 100-pin DDR DIMM slots (one open), two open CompactFlash™		
Standard	<b>2420:</b> 32 MB, <b>n/dn:</b> 64 MB	<b>2430t:</b> 48 MB, <b>tn/dtn:</b> 64 MB	
	<b>2420:</b> 288 MB, <b>n/dn:</b> 320 MB Using: Memory Enhancement technology (MEt), Double Data Rate m	2430t: 304 MB, tn/dtn: 320 MB	Q5
Print technology	Laser	ionicity iodiniology	
Print quality	Best/normal: up to 1200 x 1200 dpi	Best/normal: up to 1200 x 1200 dpi	Q5
, , , , , , , , , , , , , , , , , , ,	Draft: up to 600 x 600 dpi	Draft: up to 600 x 600 dpi	
Printer languages	HP PCL 6, HP PCL 5e, HP Postscript Level 3 Emulation, direct PDF prin	nting v 1.3 (with at least 128 MB of printer memory)	
Economical printing	Economode (saves toner), return to powersave mode after print job with the instant-on fuser technology (saves electricity), duplex and N-up printing (saves paper)		Q!
Typefaces/fonts	80 HP font set (plus Greek, Hebrew, Cyrillic, Arabic)		
Duty cycle	Up to 75,000 pages per month	Up to 100,000 pages per month	
Print margins	Top: 3 mm, left: 2 mm, right: 2 mm, bottom: 2 mm		
	Capacity Weight 100-sheet/10 envelope 60 g/m² to 200 g/m² (straight through	Size paper A4, A5, B5 (JIS), envelopes, letter, legal,	
irdy i	multipurpose tray path for special media and heavier stock		Q!
	250-sheet input tray  60 to 120 g/m²  500-sheet input tray*  60 to 120 g/m²	A4, A5, B5 (JIS), letter, legal, executive	ų.
	500-sheet input tray* 60 to 120 g/m²  Straight-through paper path for special media & heavier stock, 250-s	A4, A5, B5 (JIS), letter, legal, executive sheet top output bin, 100-sheet rear output bin.	_
	2420/n: Manual (driver support provided) 2420dn: Automatic (standard)	2430t/tn: Manual (driver support provided) 2430dtn: Automatic (standard)	Q!
Interface and connectivity	<b>2420:</b> 1 IEEE 1284-B compliant parallel port, 1 Hi-Speed USB (compatible with USB 2.0 specifications) port, 1 open EIO slot, networkable via HP Jetdirect Internal Print server	2430t: 1 IEEE 1284-B compliant parallel port, 1 Hi-Speed USB (compatible with USB 2.0 specifications) port, 1 open EIO slot, networkable via HP Jetdirect Internal	Q!
	<b>2420n/dn:</b> Same as 2420 plus HP Jetdirect Fast Ethernet Embedded Print Server	Print Server  2430tn/dtn: Same as 2430t plus HP Jetdirect Fast Ethernet Embedded Print Server	Q.
	Optional: HP Jetdirect Internal Print Servers, HP Jetdirect External Pr Card for USB/serial/LocalTalk, Bluetooth wireless		Q
Operating systems compatibility	Standard: Microsoft® Windows® 98, Me, NT 4.0 (parallel and net Apple Mac OS 9.x and later, OS X v.10.1 or later  Optional: OS/2, UNIX, Linux®, HP OpenVMS	work connections only), 2000, XP, Server 2003	Q
	Most recent printer drivers and software for all supported operating OS/2 drivers are available from IBM and are packaged with OS/	2	
Network operating systems compatibility	Standard: Via HP Jetdirect print servers: Microsoft <sup>®</sup> Windows <sup>®</sup> 98, Me, NT 4.0, 2000, XP, XP 64-bit, Server 2003; Novell NetWore 3.2, 4.2, 5.x, 6.x; Apple Mac OS 8.6 and later; Red Hat Linux <sup>®</sup> 6.x and later; SuSE Linux 6.x and later; HP-UX 10.20, 11.x; Solaris <sup>®</sup> 2.5x, 2.6, 7, 8, 9, 10 (SPARC systems only); IBM <sup>®</sup> AUX 3.2.5 and later; MPEiX, Terminal server/Citrix  Optional: Microsoft Windows NT <sup>®</sup> 4.0, 2000, XP, Server 2003; Apple Mac OS 9.x, OS X		J7
Minimum system requirements	Microsoft* Windows* 98: Pentium* 90, 16 MB RAM, CD-ROM drive; Windows NT* 4.0: Pentium 90, 32 MB RAM, CD-ROM drive; CD-ROM drive; Windows XP: 233 MHz processor, 64 MB RAM, C128 MB RAM (standard edition), 220 MB of free hard disk space IEEE 1284-compliant bidirectional parallel port, or USB 1.1, USB 2.	e; Windows 2000: 133 MHz processor, 64 MB RAM, CD-ROM drive; Windows Server 2003: 550 MHz processor, for Windows, CD-ROM drive or Internet connection,	J7 <sup>1</sup>
	Mac: 160 MB of free hard disk space for OS 9.x and Mac OS X compliant parallel port		J7
Standard software	Print drivers and installation software on CD-ROM; Microsoft <sup>®</sup> Windows <sup>®</sup> Installer, Macintosh Installer, HP PCL 6 and HP PCL 5e print drivers (Windows 95, 98, Me, NT 4.0, 2000, XP), HP Postscript Level 3 Emulation (Windows 98, Me, NT 4.0, 2000, XP, Server 2003), PostScript Printer Description files (Macintosh), Printer Dialog Extensions (Macintosh), HP LaserJet Toolbox		J6
Printer management	HP Web Jetadmin, HP LaserJet Utility, HP Embedded Web Server, E-		
Power requirements	Input voltage 100 to 127 VAC ( $\pm$ 10%), 50/60 Hz ( $\pm$ 2 Hz); 220 to 240 VAC ( $\pm$ 10%), 50/60 Hz ( $\pm$ 2 Hz) Internal power supply		
Power consumption	625 watts (printing), 11 watts (standby), 8.5 watts (powersave), 0.		Q
Dimensions (w x d x h)	Out of package: 425 x 400 x 260 mm Packaged: 592 x 495 x 347 mm	Out of package: 425 x 400 x 400 mm Packaged: 592 x 495 x 575 mm	Q:
Weight	Out of package: 16.3 kg, packaged: 19 kg	Out of package: 22 kg, packaged: 24 kg	Q
Operating environment	Operating temperature: 15 to 32.5° C, recommended operating ter recommended operating humidity: 10 to 80% RH, storage temperature Noise level per ISO 9296; Sound power: LwAd; 6.4 B(A) active, inaudible standby; Sound pressure: LpAm; bystander: 53 dB active, inaudible standby; operator: 60 dB active, inaudible standby		U3
Safety	IFC 60950 (International) FN 60950 (FU) IFC 60825-1+A1+A2 III/cIII listed (US/Canada) GS license (Furope)		НЗ
Certifications	CISPR 22: 1997/EN 55022: 1998 Class B, EN 61000-3-2: 2000 CFR, Part 15 Class B (US), ICES-003, Issue 4 (Canada), GB9254- other EMC approvals as required by individual countries		

<sup>\*</sup>The 500-sheet input tray is an optional accessory on HP LaserJet 2420 Printer series, standard with 2430 Printer series.

http://www.hp.com/uk/ http://www.hp.com

For more information, please call your local HP sales office or representative: **Austria**: 0800 242 242, **Algeria**: (0)61 56 45 43, **Bahrain**: 800 728, **Belgium**: (078) 15 20 30 (0.0496 EUR/min), **Bulgaria**: (+359) 2960 1940, **Croatia**: (+385 1) 60 60 200, **Czech Republic**: (00 420 2) 261 108 108 (Prague), **Denmark**: 48 12 10 00, **Egypt**: 532 5222, **Estonia**: (+372) 6813 823, **Finland**: (+358) 0205350 or 0205 350, **France**: (1) 69 82 6060, **Germany**: 0180 532 6222 (12 Cent/min), **Greece**: (01) 678 96 00, **Hungary**: (+36) 1 382-1111, **Iceland**: (354) 570 1000, **Ireland**: +353 1 6158200, **Israel**: (972) 9 8304848, **Italy**: (02) 92121, **Kazakhstan**: +7 (3272) 980 824, **Latria**: (371) 800 80 12, **Lithuania**: 8 800 10000 or 8 5 2103333, **Luxembourg**: (+352) 263 160 34, **Middle East**: 00971 4 883 4427, **Morocco (African Region**): +212 22 40 47 47, **Netherlands**: (020) 5476666, **Norway**: 22 735600, **Poland**: infolinia: 0-800 122 622, **Portugal**: (808) 206 001, **Romania**: (+401) 205 3300, **Russia**: +7 (095) 797 35 00, **Saudi Arabia**: 800 124 4646, **Serbia/Montenegro**: +381 11 201 99 00, **Slovakia**: +421-250222111, **Sloveni**: +3861 2307 420, **South Africa**: 0800 118 883, **Spai**: (91) 634 88 00, **Sweden**: (08) 444 2000, **Switzerland**: 0848 88 44 66, **Tunisia**: 71 891 222, **Turkey**: +90 (216) 579 71 71, **UAE**: 8004910, **UK**: 08705 474747, **Ukraine**: +380 44 490 61 20.















One-year limited warranty, return to HP/dealer, optional HP Care Pack available

## Ordering information

HP LaserJet 2420 Printer series
5956A HP LaserJet 2420 Printer,
power cord, control panel overlay
(included only when needed to
change the language on the control
panel for a country/region), print
cartridge, software and documentation
on CD-ROM, start guide, support flyer

Q5958A HP LaserJet 2420n Printer, as above plus: HP Jetdirect Fast Ethernet Embedded Print Server Q5959A HP LaserJet 2420dn Printer, as above plus: buil-in automatic two-sided printing

#### HP LaserJet 2430 Printer series

Q5960A HP LaserJet 2430t Printer,
500-sheet input tray (tray 3),
power cord, control panel overlay
(included only when needed to
change the language on the control
panel for a country/region), print
cartridge, software and documentation
on CD-ROM, start guide, support flyer
Q5961A HP LaserJet 2430t Printer,

as above plus: HP Jetdirect Fast Ethernet Embedded Print Server

Q5962A HP LaserJet 2430dtn Printer, as above plus: built-in automatic two-sided printing

Accessories
5963A 500-sheet input tray

Supplies

Q6511A HP LaserJet smart print cartridge (6,000 pages)\*
Q6511X HP LaserJet smart print

cartridge (12,000 pages)\*

\*Declared yield value in accordance with
ISO/IEC 19752

Connectivity

J7934A HP Jetdirect 620n Fast Ethernet Internal Print Server J7960A HP Jetdirect 625n Gigabit Ethernet Internal Print Server

J7958A HP Jetdirect 680n 802.11b Internal Print Server

J7951A HP Jetdirect ew2400 802.11g Wireless and Fast Ethernet External Print Server (USB 2.0)

6072A HP bt1300 Bluetooth Wireless Printer Adaptor (USB or parallel)

To view the complete range of connectivity options please visit http://www.hp.com

Q3982A 32 MB 100-pin DDR DIMM
Q2625A 64 MB 100-pin DDR DIMM
Q2626A 128 MB 100-pin DDR DIMM
Q2626A 128 MB 100-pin DDR DIMM

 Q2627A
 256 MB 100-pin DDR DIMM

 Service & support
 U3790A/E

 HP Care Pack, 3-year,

u3791A/E HP Care Pack, 3-year, next business day on-site
H3110E Installation & network configuration for 1 network printer